

# **DIGITAL CAMERA HAVING AN ELECTRONIC ZOOM FUNCTION**

This application is based on Patent Application  
No. 11-354565 filed in Japan, the content of which is  
hereby incorporated by reference.

## **BACKGROUND OF THE INVENTION**

### **FIELD OF THE INVENTION**

The present invention relates to a digital  
camera provided with a zoomable optical finder and  
electronic finder having an electronic zoom function.  
The present invention further relates to a recording  
medium for recording programs readable by the digital  
camera.

### **DESCRIPTION OF THE RELATED ART**

Most digital cameras have a finder for  
electrically displaying an image via liquid crystal  
device (LCD) or the like (hereinafter referred to as  
"electronic finder"). However, in such digital cameras,  
the electronic finder juxtaposed with an optical finder  
is optionally turned ON/OFF via a switch in order to  
prevent battery power consumption.

Digital cameras are known which are provided  
with a electronic zoom function of about 2x without

deterioration of image quality in order to enlarge a photographic object while maintaining the compactness of the camera. Since the field of view of the optical finder does not match the actual photographic range during electronic zooming, a field of view frame is displayed in the optical finder during electronic zooming.

Although it is possible to associate the field of view of the optical finder with the actual photographic range in this way, a disadvantage arises in that it is difficult to confirm a photographic subject simply by displaying the photographic range with a simple field of view frame because the subject cannot be optically displayed in enlargement.

Japanese Laid-Open Patent Application No. H6-189173 discloses a digital camera wherein a finder optical system zooms in response to electronic zooming. This application discloses a digital camera provided with an actual zoom function of up to 6x by using together a 3x optical zoom and a 2x electronic zoom, thereby having an optical finder with a 6x zoom ratio corresponding to the combined 6x zoom ratio.

According to this art, however, although the photographic subject is easily confirmed and framing is easily accomplished, the optical finder is provided a zoom function corresponding to the effective zoom

function. Accordingly, the optical finder is larger and heavier, and disadvantageously interferes with the compactness of the camera.

An object of the present invention is to  
5 eliminate the disadvantages of the conventional art by providing a digital camera and recording medium allowing easy confirmation of a photographic object and easy framing without interfering with the compactness of the digital camera.

#### SUMMARY OF THE INVENTION

These objects are attained by the digital camera of the present invention comprising: an optical finder for optically viewing a photographic object; an  
10 electronic finder for electronically displaying a photographic object; an operation member for performing an electronic zoom; a switching member for switching between an activated state and a deactivated state of the electronic finder; and a controller for setting the  
15 electronic finder to the activated state forcedly when the electronic zoom is performed by the operation member.

These objects are further attained by another digital camera of the present invention comprising: an optical finder for optically viewing a photographic  
20 object; an electronic finder for electronically

displaying a photographic object; an operation member for performing an electronic zoom; a switching member for switching between an activated state and a deactivated state of the electronic finder; a zooming lens for image  
5 sensing; and a controller for setting the electronic finder to the activated state forcedly when an effective magnification of one or both an optical zoom of said zoom lens or said electronic zoom exceeds a magnification range of said optical finder.

10 These objects are further attained by another digital camera of the present invention comprising: an optical finder for optically viewing a photographic object; an electronic finder for electronically displaying a photographic object; an operation member for performing an electronic zoom; a switching member for  
15 switching between an activated state and a deactivated state of the electronic finder; a setter for setting a magnification for image sensing when the digital camera is activated; and a controller for setting said  
20 electronic finder to the activated state when said magnification is determined to be outside a magnification range of the optical finder.

25 These objects are further attained by another digital camera of the present invention comprising: an optical finder for optically viewing a photographic

object; an electronic finder for electronically displaying a photographic object; an operation member for performing an electronic zoom; a setter for setting a magnification for image sensing when the digital camera is activated; and an indicator for indicating a warning when said magnification is outside a magnification range of the optical finder.

These objects are further attained by A recording medium in which a program to be executed by the digital camera having an optical finder for optically viewing a photographic object, an electronic finder for electronically displaying a photographic object, an operation member for performing an electronic zoom, and a switching member for switching between an activated state and a deactivated state of the electronic finder is recorded and which can be read by a computer, said program implementing: performing the electronic zoom by said operation member; and setting said electronic finder to the activated state forcedly when the electronic zoom is performed.

#### BRIEF DESCRIPTION OF THE DRAWINGS

In the following description, like parts are designated by like reference numbers throughout the several drawings.

FIG. 1 is a front view of a digital camera of an embodiment of the present invention;

FIG. 2 is a back view of a digital camera of an embodiment of the present invention;

5 FIG. 3 is a side view of a digital camera of an embodiment of the present invention;

FIG. 4 is a bottom view of a digital camera of an embodiment of the present invention;

FIG. 5 is a block diagram showing the internal structure of the digital camera of an embodiment of the present invention;

FIG. 6 shows the internal structure of the optical finder;

FIG. 7 is a block diagram showing the structure of the image processor;

FIG. 8 shows the condition of the electronic zoom process;

FIG. 9 is a flow chart showing the processing sequence from power ON to power OFF;

FIG. 10 is a flow chart showing the initialization process sequence;

FIG. 11 is a flow chart showing the zoom process sequence during the photography standby;

FIG. 12 is a flow chart showing the process of LCD automatic display control;

FIG. 13 is a flow chart showing the LCD ON/OFF control process sequence;

FIG. 14 is a flow chart showing the warning LED control process sequence; and

FIG. 15 shows a modification of the warning means.

#### **DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS**

The preferred embodiments of the present invention are described hereinafter with reference to the accompanying drawings.

FIGS. 1 through 4 respectively show a front view, back view, side view, and bottom view of a digital camera 1 of an embodiment of the present invention. FIG. 5 is a block diagram showing the internal structure of the digital camera 1.

The digital camera 1 comprises a box-like camera body 2, and a rectangular image sensing unit 3 (indicated by the thick lines in FIGS. 1, 2, and 4) as shown in FIG. 1. The image sensing unit 3 has a macro function zoom lens 301 acting as a taking lens, and is provided with an image sensing circuit 302 having a CCD 303 (refer to FIG. 5) acting as a 1/2 inch size CCD color area sensor disposed at a suitable position behind the zoom lens 301. The zoom lens 301 has a focal length of 7

mm in the wide state and 21 mm in the telecentric state, and has a zoom ratio of 3x. The digital camera 1 is capable of a maximum 6x zoom photography via an electronic zoom function described later.

5           A light adjusting control circuit 304 having a light adjusting control sensor 305 for receiving the reflected light of the flash from the photographic object is provided at a suitable location within the image sensing unit 3 similar to a camera using silver halide film. In addition, a distance measuring sensor 306 for measuring the distance to a photographic object and an optical finder 31 are provided at suitable locations within the image sensing unit 3. The internal structure of the optical finder 31 is described later.

10  
15           On the front surface of the camera body 2 is provided a grip 4 on the left end and a built-in flash 5 on the top center, and a shutter button 8 is provided on the top surface, as shown in FIG. 1.

20           On the back surface of the camera body 2 is provided an LCD 10 as a photographic image monitor display (equivalent to a viewfinder), and for displaying the recorded images at the approximate center of the back surface as shown in FIG. 2. The LCD 10 is equivalent to an electronic viewfinder. Below the LCD 10 are provided  
25           key switches 221-226 for operating the digital camera 1,



and a power switch 227. On the left side of the power switch 227 are arranged an LED 228 which lights when the power is ON, and an LED 229 which displays while a memory card is being accessed.

5               Also on the back surface of the camera body 2 is a mode setting switch 14 for selecting among [photographic mode], [reproduction mode], and [preference mode] (refer to FIG. 2). The photographic mode is used for taking photographs. The reproduction mode is a mode for reproducing a photographed image recorded on a memory card and displaying the image on the LCD 10. The preference mode is a mode for settings of various types by selecting a desired item from among display items (setting items). The operations in each mode are described later.

10              The mode setting switch 14 is a contact point slide switch and sets the photographic mode when at the bottom, sets the reproduction mode at the center, and sets the preference mode at the top, as shown in FIG. 2.

15              A 4-point switch 230 is provided on the right side of the back surface of the camera. In the photographic mode, a zoom motor 307 (refer to FIG. 5) drives the zoom lens 301 for zooming by pressing the buttons 231 and 232. The zoom lens 301 is driven to the

wide side when button 231 is pressed, and driven to the telecentric side when the button 232 is pressed.

On the back of the image sensing unit 3 are provided an LCD button 321 for turning ON and OFF the LCD 10, and a macro button 322. When the LCD button 321 is pressed, the LCD display is switched ON or OFF. For example, during photography using only the optical finder 31, the LCD display is switched OFF to conserve power. When the macro button 322 is pressed during macro photography, an AF motor 308 (refer to FIG. 5) is driven to place the zoom lens 301 in the macro photography enabled state.

On the side of the camera body 2 is provided a pin unit 235, as shown in FIG. 3. The pin unit 235 is provided with a DC input pin 235a, and a video-out pin 235b for outputting the content displayed on the LCD 10 to an external video monitor.

On the bottom surface of the camera body 2 are provided a battery compartment 18 for loading a battery, and a card compartment 17, as shown in FIG. 4. The card compartment 17 has a slot-shaped insertion opening used for inserting a memory card 91 within the camera body 2 to allow writing and reading of image data to/from the memory card 91. Both compartments can be opened and closed using a clam-shell type door. FIG. 4 shows an

example with a memory card 91 installed in the card compartment 17.

In the digital camera 1, four AA-size dry cell batteries are installed in the battery compartment 18, and connected in series as to form the power source battery 236 (refer to FIG. 5) which is used as the drive source. Of course, electric power also may be supplied from an adapter using the DC input pin 235a shown in FIG. 4.

The bottom surface is also provided with release lever 19 for releasing the connection between the image sensing unit 3 and the camera body 2 which are connected by a connector and key-like connecting member.

The internal structure of the image sensing unit 3 is described below with reference to FIG. 5.

The image sensing circuit 302 photoelectrically converts an optical image of the photographic object formed on the CCD 303 by the zoom lens 301 using the CCD 303, and outputs the image as red (R), green (G), blue (B) color component image signals (signals comprising a signal series of pixel signals of the light received by each pixel).

Since the diaphragm is fixed in the digital camera 1, exposure control in the image sensing unit 3 is accomplished by regulating the amount of exposure light

of the CCD 303 (i.e., the load accumulation time of the  
CCD 303 corresponding to shutter speed). When a suitable  
shutter speed cannot be set when the photographic object  
luminance is a low luminance, unsuitable exposure due to  
5 insufficient exposure light can be corrected by adjusting  
the level of the image signal output from the CCD 303.  
That is, during times of low luminance, exposure can be  
controlled by combining shutter speed and gain adjustment.  
The image signal level adjustment is accomplished by the  
auto gain control circuit (AGC) within a signal  
processing circuit 313 described later.

A timing generator 314 generates a drive  
control signal for the CCD 303 based on a clock signal  
transmitted from a timing control circuit 202 within the  
camera body 2. The timing generator 314 generates clock  
15 signals, for example, such as a storage start/end timing  
signal (i.e., exposure start/end), read control signal  
(horizontal synchronization signal, vertical  
synchronization signal, transfer signal and the like) of  
each pixel photoreception signal and the like, and  
20 outputs these signals to the CCD 303.

The signal processing circuit 313 performs  
specific analog signal processing of image signals  
(analog signals) output from the image sensing circuit  
25 302. The signal processing circuit 313 includes a

correlation double sampling (CDS) circuit and an auto gain control (AGC) circuit, and reduces the noise of the image signals via the CDS circuit, and adjusts the level of the image signals by adjusting the gain via the AGC circuit.

The light adjusting control circuit 304 controls the amount of light emitted by the built-in flash 5 during flash photography to the specific amount of light emission set by the general controller 211 of the camera body 2. When the amount of received light attains the specific amount of emission light, a flash stop signal is output from the light adjusting control circuit 304 to the flash control circuit 214 via the general controller 211. The flash control circuit 214 forcibly stops light emission by the built-in flash 5 in response to the emission stop signal, and in this way the amount of light emitted from the flash 5 is controlled to the specific emission amount.

Within the image sensing unit 3 are provided a zoom motor 307 for moving the lens between a housed position and photography position and for changing the zoom ratio of the zoom lens 301, and an autofocus (AF) motor 308 for focus adjustment, and a finder motor 311 for moving the lens to change the zoom ratio of the optical finder.

FIG. 6 shows the internal structure of the optical finder 31; FIG. 6(a) shows the telecentric state, and FIG. 6(b) shows the wide state. The optical finder 31 is provided with a finder zoom lens comprising objective lens 310a, lens 310b and an eyepiece lens 310c as a finder optical system, and the magnification is changed by moving the lens 310b in the optical axis direction via the drive of the finder motor 311. The magnification of the finder zoom lens 310 is limited, and in the present embodiment the obtainable magnification is between 1.0~3.0.

A warning LED 312 is provided within the optical finder 31 which warns by lighting with a specific timing described later. A photographer looking through the optical finder 31 easily becomes aware of the switch from the optical finder to the electronic finder by seeing the lighted warning LED 312.

Referring back to FIG. 5, the internal structure of the camera body 2 is described below.

The general controller 211 mainly comprises a CPU, and controls each peripheral structure of the camera body 2 and the interior of the image sensing unit 3 connected by address bus, data bus, and control bus, and performs general control of photographic operations of the digital camera 1.

The flow of the image data in FIG. 5 (and FIG. 7 described later) is indicated by arrows between the peripheral structures, but actually the image data are transmitted to each peripheral structure through the general controller 211. For this reason within the general controller 211 are provided a DRAM work RAM M211a, a flash ROM 211b for storing control programs, previous magnification when the power is OFF and previous condition of the LCD when the power is OFF, and an expansion processor 211c for a thinness process and interpolation process described later.

Image signal processing within the camera body 2 and structures relating to image display are described below.

Analog image signals transmitted from the signal processing circuit 312 of the image sensing unit 3 are subjected to various image processing in the image processor 200 within the camera body 2. FIG. 7 is a block diagram showing the structure of the image processor 200. First, the analog image signal transmitted to the image processor 200 is converted to a 10-bit digital signal for each pixel in the A/D converter 205. The A/D converter 205 converts each pixel signal (analog signal) to a 10-bit digital signal based on the

clock signal of the A/D converter input from the timing control circuit 202.

The timing control circuit 202 generates a standard clock signal, and clock signals for the timing generator 314 and A/D converter 205 via control by the general controller 211.

A black level correction circuit 206 corrects the black level the A/D converted pixel signal (hereinafter referred to as "pixel data") to a standard black level. A WB circuit 207 performs level conversion of the pixel data of each color component R, G, B, and adjusts the white balance in consideration of gamma correction in a later process. The white balance adjustment is accomplished using a level conversion table (properly speaking, the data of the table) input from the general controller 211 to the WB circuit, and the conversion coefficient (characteristics slope) of each color component of the level conversion table is set for each photographic image by the general controller 211.

A gamma correction circuit 208 corrects the gamma characteristic of the pixel data. The output from the gamma correction circuit 208 is transmitted to an image memory 209 as shown in FIG. 5.

The image memory 209 is a memory for storing pixel data output from the image processor 200, and has a



1-frame memory capacity. That is, the image memory 209 has a memory capacity sufficient to store pixel data of  $n \times m$  pixels when the CCD 303 has pixels arrayed in a matrix of  $n$  lines and  $m$  columns (where  $n$  and  $m$  are natural numbers), and stores the pixel data in a corresponding memory area (address).

A VRAM 210 is a buffer memory for image data reproduced and displayed on the LCD 10. The VRAM 210 has a memory capacity sufficient to store image data corresponding to the number of pixels of the LCD 10.

According to this construction, in the photography standby state in the photographic mode, pixel data of an image sensed at specific intervals by the image sensing unit 3 are processed by the image processor 200, and stored in the image memory 209. The image data are subjected to a thinness process described later in accordance with the magnification set by pressing the buttons 231 and 232 (hereinafter referred to as "set magnification"), and thereafter transferred to the VRAM 210, and displayed on the LCD 10 (live view display). In this way the photographer is able to visually confirm an object image via the image displayed on the LCD 10.

In the reproduction mode, after the image read from the memory card has been subjected to specific signal processing by the general controller 211, the data

are transmitted to the VRAM 210 and reproduced and displayed on the LCD 10. When an image is displayed on the LCD 10, a backlight 16 is lighted via control by the general controller 211.

5                   Another structure within the camera body 2 is described below.

10                   A card I/F 212 is an interface for bi-directional communication with various types of memory cards installed in the card compartment 17. Specifically, writing image data to the memory card, and reading image data from the memory card.

15                   A flash control circuit 214 is a circuit for controlling the emission of the built-in flash 5. The flash control circuit 214 controls the emission or lack thereof, emission amount, and emission timing of the built-in flash 5 based on control signals from the general controller 211, and controls the amount of emission of the built-in flash 5 based on an emission stop signal input from the light adjusting control  
20                   circuit 304.

                  A clock circuit 219 manages the photograph date and time, and is driven by a separate battery not shown in the drawings.

25                   Within the camera body 2 are provided a zoom motor drive circuit 215 and AF motor drive circuit 216

for driving the zoom motor 307 and the AF motor 308. These circuits function by the operation of an operating portion 250 of a shutter button 8 and various other types of switches and buttons described later.

5               For example, the shutter button 8 is a two-stage switch capable of detecting the half-depression state, and full-depression state used by cameras using silver halide film (hereinafter referred to as "silver halide camera"). When the shutter button 8 is depressed half way in the photography standby state, distance information from the distance measuring sensor 306 is input to the general controller 211. Then, the AF motor drive circuit 216 drives the AF motor 308 by instructions from the general controller 211, so as to move the zoom lens 301 to the focus position.

10               When buttons 231 and 232 are pressed, signals from these buttons are transmitted to the general controller 211, and the general controller 211 specifies the set magnification obtained from the signal. The zoom motor drive circuit 215 drives the zoom motor 307 by means of the aforesaid instruction, so as to move the zoom lens and accomplish zooming. Then, the electronic zoom process described later is executed by the expansion processor 211c. In this way the effective magnification matches the set magnification, with the effective

15  
20  
25

magnification being the actual magnification during live view or photography.

Although the various structures within the camera body 2 have been described above, the general controller 211 accomplishes various other functions such as timing control and transfer of data with peripheral structures through software.

For example, the general controller 211 is provided with a luminance determination function for setting an exposure control value (shutter speed), and a shutter speed setting function. The luminance determination function determines the brightness of a photographic object using the image stored in the image memory 209 and captured every  $1/30^{\text{th}}$  second by the CCD 303 in the photography standby state. The shutter speed setting function sets the shutter speed (accumulation time of the CCD 303) based on the object brightness determination result of the luminance determination.

The general controller 211 is provided with a filtering process function, recorded image generation function, and reproduction image generation function to accomplish the photographic image recording process.

The filtering process function corrects the high frequency component of the image being recorded via

a digital filter to correct image quality relating to contour.

The recording image generation function reads the pixel data from the image memory 209, and generates a thumbnail image and compressed image to be recorded on the memory card. Specifically, pixel data are read for each 8 pixels in both horizontal and vertical directions while scanning from the image memory 209 in the raster scan direction. Next, a thumbnail image is generated and transferred to the memory card and recorded on the memory card. When recording the compressed image data on the memory card, all pixel data are read from the image memory 209, subjected a specific compression processing by a JPEG method such as Hoffman coding or two-dimensional DCT conversion, and recorded on the memory card.

The specific operation is described below.

When a photograph is specified by the shutter button 8 in the photography mode, a thumbnail image of the image in the image memory 209 is generated, and a compressed image compressed by a JPEG method is generated based on the set compression ratio, and both images together with tag information relating to the photographed image (information such as frame number, exposure value, shutter speed, compression ratio, date, time, flash

ON/OFF data, scene information, image determination result and the like) are recorded on the memory card.

The reproduction image generation function generates a reproduced image by expanding the compressed image recorded on the memory card. The specific operation is described below. When the mode setting switch 14 sets the reproduction mode, the image data of the highest frame number in the memory card are read and expanded, and transferred to the VRAM 210. In this way the image of the highest frame number, i.e., the latest photographed image, is displayed on the LCD 10.

As shown in FIG. 5, when the memory card 91 is loaded in the card compartment 17 and processing described later is executed, the general controller 211 performs controls of the various parts described later, and normally, the control programs are installed in the flash ROM within the general controller 211. However, other control programs and update programs for updating the control programs may be recorded on a recording medium such as the set-up memory card 92 which is loaded in the card compartment 17, such that the control programs and update programs can be read and installed from the set-up memory card 92.

The various processes of the digital imaging device of the present invention are described below.

FIG. 8 shows the condition of the electronic zoom process. In the digital camera 1 of the present embodiment, when the set magnification is greater than a specific magnification, specifically, when the set magnification is greater than the upper limit magnification (zoom ratio) 3.0x of the zoom lens 301, the optical zoom of 3.0x of the zoom lens is used together with the electronic zoom. The electronic zoom process is described below.

First, the thinness process is described which is an electronic zoom process in live view. As shown in FIG. 8, in 2x zooming, for example, a 1/2 thinness process is performed on image data of an area of 800x600 pixels in the center area among the 1600x1200 pixel image data within the image memory 209, to derive image data of 400x300 pixels, which are stored in the VRAM 210. In this way the image data of 400x300 pixels stored in the VRAM 210 are displayed on the LCD 10.

Similarly, during electronic zooming in live view, an  $\text{Int}(x/4)$  thinness process is performed on image data of region CA of  $\text{Int}(1600/x) \times \text{Int}(1200/x)$  in the center area of the image data ID1 of 1600x1200 pixels (in the present embodiment, x is a number equal to or greater than 1 but less than 2, in steps of 0.1 as one step), to derive image data ID2 of 400x300 pixels which are stored

in the VRAM 210 and displayed on the LCD 10.  $\text{Int}(a)$  is a function representing the area of integer  $a$ .

In the electronic zoom during live view, only image data of area CA corresponding to the set magnification are read in the center of the image data in the image memory 209, culled according to the number of pixels of the LCD 10, and displayed.

The electronic zoom process during photography is described below. When photographing at 2x electronic zoom, a 2x linear interpolation process is performed on the image data of area CA of 800x600 pixels in the center area of the image data ID1 of 1600x1200 pixels in the image memory 209, and the data are stored in again in image memory 209 as 1600x1200 pixel image data ID3, and thereafter subjected to the previously mentioned compression process and the like and recorded on the memory card.

Similarly, when using X-magnification electronic zooming during photography, an X-magnification linear interpolation process is performed on image data within the  $\text{Int}(1600/x) \times \text{Int}(1200/x)$  in the center area of the image data of 1600x1200 pixels, and the data are again stored in image memory 209 as 1600x1200 pixel image data, then subjected to the previously mentioned



compression process and the like and recorded on the memory card.

In this way in electronic zooming during photography, only the image data of area CA corresponding to the set magnification are read from the center of the image data in the image memory 209, interpolation is performed to obtain image data identical to the original number of pixels, and again stored in image memory 209, and after the previously described processing, the data are recorded on the memory card.

The thinness process and interpolation process are accomplished by the expansion processor 211c of the general controller 211 using the work RAM 211a of the general controller 211 and the image memory 209.

Processes performed from the switching ON of power to the switching OFF of power in the digital camera of the present embodiment are described below.

FIG. 9 is a flow chart showing the sequence of processing after power is turned ON until power is turned OFF in the digital camera 1 of the present embodiment. The first process is the initialization process. (step S1).

FIG. 10 is a flow chart showing the sequence of the initialization process. In the initialization process, first, other initialization processes are

executed (step S101). Specifically, the work RAM 211a, VRAM 210, and image memory 209 are initialized. Then, when the set magnification at the previous power OFF is greater than 3.0x, the LCD 10 is forcibly turned ON  
5 because the electronic zoom is used. Furthermore, the warning LED 312 is lighted when the electronic zoom is used in the warning LED control of the main routine. The set magnification when the power was previously turned OFF is the effective magnification at the previous power OFF.

Next, the set magnification (effective magnification) at the previous power OFF recorded in the flash ROM 211b is read (step S102). That is, in the present embodiment, the set magnification at actuation is  
10 15 identical to the set magnification at the previous power OFF, and for this reason the set magnification at the previous power OFF recorded in the flash ROM 211b when the camera was last used (i.e., the process of step S7 described later) is read out from memory.

20 Then, a determination is made as to whether or not the set magnification of the previous power OFF is greater than 3.0x (step S103), and if the set magnification is greater than 3.0x, the routine advances to step S104, whereas when the set magnification is not  
25 greater than 3.0x, the routine advances to step S108.

The following process is executed when the set magnification at the previous power OFF is greater than 3,0x.

First, the read set magnification of the previous power OFF is set, and electronic zooming is executed in accordance with the set magnification (step S104). That is, electronic zooming is performed at a magnification of the set magnification divided by 3.0.

Then the zoom lens 301 is moved to the 3.0x position by the drive of the zoom motor 307 (step S105). That is, the effective magnification of both the optical zoom and electronic zoom are set to equal the set magnification (greater than 3.0x).

Then, the finder zoom lens 310 is moved to the 3.0x position by the drive of the finder motor 311 (step S106). Then, the LCD 10 is turned ON (step S107). In this way the LCD 10 displays image data subjected to the previously described thinness process. The process ends when the set magnification greater than 3.0x has been set.

The process when the set magnification of the previous power OFF is less than 3.0x is determined in step S103 is described below.

First, the zoom lens 301 is moved to the position corresponding to the set magnification by the drive of the zoom motor 307 (step S108). Then, the

finder zoom lens 310 is moved to the position corresponding to the set magnification by the drive of the finder motor 311 (step S109). The effective magnification is then equal to the set magnification.

5               Next, the ON/OFF state of the LCD 10 recorded in the flash ROM 211b at the previous power OFF is read (step S110).

              Then, a determination is made as to whether or not the LCD 10 was OFF at the previous power OFF (step S112). When the LCD 10 was ON, the routine advances to step S107, and the LCD 10 is turned ON. Conversely, when the LCD 10 was OFF, the initialization process ends.

              Referring to FIG. 9, the zoom process for photography standby (live view) is executed (step S2).

10  
20  
30  
40  
50  
60  
70  
80  
90  
100  
110  
120  
130  
140  
150  
160  
170  
180  
190  
200  
210  
220  
230  
240  
250  
260  
270  
280  
290  
300  
310  
320  
330  
340  
350  
360  
370  
380  
390  
400  
410  
420  
430  
440  
450  
460  
470  
480  
490  
500  
510  
520  
530  
540  
550  
560  
570  
580  
590  
600  
610  
620  
630  
640  
650  
660  
670  
680  
690  
700  
710  
720  
730  
740  
750  
760  
770  
780  
790  
800  
810  
820  
830  
840  
850  
860  
870  
880  
890  
900  
910  
920  
930  
940  
950  
960  
970  
980  
990  
1000  
1010  
1020  
1030  
1040  
1050  
1060  
1070  
1080  
1090  
1100  
1110  
1120  
1130  
1140  
1150  
1160  
1170  
1180  
1190  
1200  
1210  
1220  
1230  
1240  
1250  
1260  
1270  
1280  
1290  
1300  
1310  
1320  
1330  
1340  
1350  
1360  
1370  
1380  
1390  
1400  
1410  
1420  
1430  
1440  
1450  
1460  
1470  
1480  
1490  
1500  
1510  
1520  
1530  
1540  
1550  
1560  
1570  
1580  
1590  
1600  
1610  
1620  
1630  
1640  
1650  
1660  
1670  
1680  
1690  
1700  
1710  
1720  
1730  
1740  
1750  
1760  
1770  
1780  
1790  
1800  
1810  
1820  
1830  
1840  
1850  
1860  
1870  
1880  
1890  
1900  
1910  
1920  
1930  
1940  
1950  
1960  
1970  
1980  
1990  
2000  
2010  
2020  
2030  
2040  
2050  
2060  
2070  
2080  
2090  
2100  
2110  
2120  
2130  
2140  
2150  
2160  
2170  
2180  
2190  
2200  
2210  
2220  
2230  
2240  
2250  
2260  
2270  
2280  
2290  
2300  
2310  
2320  
2330  
2340  
2350  
2360  
2370  
2380  
2390  
2400  
2410  
2420  
2430  
2440  
2450  
2460  
2470  
2480  
2490  
2500  
2510  
2520  
2530  
2540  
2550  
2560  
2570  
2580  
2590  
2600  
2610  
2620  
2630  
2640  
2650  
2660  
2670  
2680  
2690  
2700  
2710  
2720  
2730  
2740  
2750  
2760  
2770  
2780  
2790  
2800  
2810  
2820  
2830  
2840  
2850  
2860  
2870  
2880  
2890  
2900  
2910  
2920  
2930  
2940  
2950  
2960  
2970  
2980  
2990  
3000  
3010  
3020  
3030  
3040  
3050  
3060  
3070  
3080  
3090  
3100  
3110  
3120  
3130  
3140  
3150  
3160  
3170  
3180  
3190  
3200  
3210  
3220  
3230  
3240  
3250  
3260  
3270  
3280  
3290  
3300  
3310  
3320  
3330  
3340  
3350  
3360  
3370  
3380  
3390  
3400  
3410  
3420  
3430  
3440  
3450  
3460  
3470  
3480  
3490  
3500  
3510  
3520  
3530  
3540  
3550  
3560  
3570  
3580  
3590  
3600  
3610  
3620  
3630  
3640  
3650  
3660  
3670  
3680  
3690  
3700  
3710  
3720  
3730  
3740  
3750  
3760  
3770  
3780  
3790  
3800  
3810  
3820  
3830  
3840  
3850  
3860  
3870  
3880  
3890  
3900  
3910  
3920  
3930  
3940  
3950  
3960  
3970  
3980  
3990  
4000  
4010  
4020  
4030  
4040  
4050  
4060  
4070  
4080  
4090  
4100  
4110  
4120  
4130  
4140  
4150  
4160  
4170  
4180  
4190  
4200  
4210  
4220  
4230  
4240  
4250  
4260  
4270  
4280  
4290  
4300  
4310  
4320  
4330  
4340  
4350  
4360  
4370  
4380  
4390  
4400  
4410  
4420  
4430  
4440  
4450  
4460  
4470  
4480  
4490  
4500  
4510  
4520  
4530  
4540  
4550  
4560  
4570  
4580  
4590  
4600  
4610  
4620  
4630  
4640  
4650  
4660  
4670  
4680  
4690  
4700  
4710  
4720  
4730  
4740  
4750  
4760  
4770  
4780  
4790  
4800  
4810  
4820  
4830  
4840  
4850  
4860  
4870  
4880  
4890  
4900  
4910  
4920  
4930  
4940  
4950  
4960  
4970  
4980  
4990  
5000  
5010  
5020  
5030  
5040  
5050  
5060  
5070  
5080  
5090  
5100  
5110  
5120  
5130  
5140  
5150  
5160  
5170  
5180  
5190  
5200  
5210  
5220  
5230  
5240  
5250  
5260  
5270  
5280  
5290  
5300  
5310  
5320  
5330  
5340  
5350  
5360  
5370  
5380  
5390  
5400  
5410  
5420  
5430  
5440  
5450  
5460  
5470  
5480  
5490  
5500  
5510  
5520  
5530  
5540  
5550  
5560  
5570  
5580  
5590  
5600  
5610  
5620  
5630  
5640  
5650  
5660  
5670  
5680  
5690  
5700  
5710  
5720  
5730  
5740  
5750  
5760  
5770  
5780  
5790  
5800  
5810  
5820  
5830  
5840  
5850  
5860  
5870  
5880  
5890  
5900  
5910  
5920  
5930  
5940  
5950  
5960  
5970  
5980  
5990  
6000  
6010  
6020  
6030  
6040  
6050  
6060  
6070  
6080  
6090  
6100  
6110  
6120  
6130  
6140  
6150  
6160  
6170  
6180  
6190  
6200  
6210  
6220  
6230  
6240  
6250  
6260  
6270  
6280  
6290  
6300  
6310  
6320  
6330  
6340  
6350  
6360  
6370  
6380  
6390  
6400  
6410  
6420  
6430  
6440  
6450  
6460  
6470  
6480  
6490  
6500  
6510  
6520  
6530  
6540  
6550  
6560  
6570  
6580  
6590  
6600  
6610  
6620  
6630  
6640  
6650  
6660  
6670  
6680  
6690  
6700  
6710  
6720  
6730  
6740  
6750  
6760  
6770  
6780  
6790  
6800  
6810  
6820  
6830  
6840  
6850  
6860  
6870  
6880  
6890  
6900  
6910  
6920  
6930  
6940  
6950  
6960  
6970  
6980  
6990  
7000  
7010  
7020  
7030  
7040  
7050  
7060  
7070  
7080  
7090  
7100  
7110  
7120  
7130  
7140  
7150  
7160  
7170  
7180  
7190  
7200  
7210  
7220  
7230  
7240  
7250  
7260  
7270  
7280  
7290  
7300  
7310  
7320  
7330  
7340  
7350  
7360  
7370  
7380  
7390  
7400  
7410  
7420  
7430  
7440  
7450  
7460  
7470  
7480  
7490  
7500  
7510  
7520  
7530  
7540  
7550  
7560  
7570  
7580  
7590  
7600  
7610  
7620  
7630  
7640  
7650  
7660  
7670  
7680  
7690  
7700  
7710  
7720  
7730  
7740  
7750  
7760  
7770  
7780  
7790  
7800  
7810  
7820  
7830  
7840  
7850  
7860  
7870  
7880  
7890  
7900  
7910  
7920  
7930  
7940  
7950  
7960  
7970  
7980  
7990  
8000  
8010  
8020  
8030  
8040  
8050  
8060  
8070  
8080  
8090  
8100  
8110  
8120  
8130  
8140  
8150  
8160  
8170  
8180  
8190  
8200  
8210  
8220  
8230  
8240  
8250  
8260  
8270  
8280  
8290  
8300  
8310  
8320  
8330  
8340  
8350  
8360  
8370  
8380  
8390  
8400  
8410  
8420  
8430  
8440  
8450  
8460  
8470  
8480  
8490  
8500  
8510  
8520  
8530  
8540  
8550  
8560  
8570  
8580  
8590  
8600  
8610  
8620  
8630  
8640  
8650  
8660  
8670  
8680  
8690  
8700  
8710  
8720  
8730  
8740  
8750  
8760  
8770  
8780  
8790  
8800  
8810  
8820  
8830  
8840  
8850  
8860  
8870  
8880  
8890  
8900  
8910  
8920  
8930  
8940  
8950  
8960  
8970  
8980  
8990  
9000  
9010  
9020  
9030  
9040  
9050  
9060  
9070  
9080  
9090  
9100  
9110  
9120  
9130  
9140  
9150  
9160  
9170  
9180  
9190  
9200  
9210  
9220  
9230  
9240  
9250  
9260  
9270  
9280  
9290  
9300  
9310  
9320  
9330  
9340  
9350  
9360  
9370  
9380  
9390  
9400  
9410  
9420  
9430  
9440  
9450  
9460  
9470  
9480  
9490  
9500  
9510  
9520  
9530  
9540  
9550  
9560  
9570  
9580  
9590  
9600  
9610  
9620  
9630  
9640  
9650  
9660  
9670  
9680  
9690  
9700  
9710  
9720  
9730  
9740  
9750  
9760  
9770  
9780  
9790  
9800  
9810  
9820  
9830  
9840  
9850  
9860  
9870  
9880  
9890  
9900  
9910  
9920  
9930  
9940  
9950  
9960  
9970  
9980  
9990  
10000

              In step S2, when the button 231 is pressed, the zoom magnification is decreased one step, and when the button 232 is pressed, the zoom magnification is increased one step. Electronic zoom is used when the set magnification is greater than 3.0x.

20               The zoom process during photography standby is described below. FIG. 11 is a flow chart showing the sequence of the zoom process during photography standby.

              First, a determination is made as to whether or not button 232 has been pressed (step S201); if the  
25               button 232 has been pressed, the routine advances to step

S202, whereas if the button 232 has not been pressed, the routine advances to step S208.

The process when button 232 has been pressed is described below. First, a determination is made as to whether or not the current set magnification is 6.0x (step S202). If the set magnification is 6.0x, the zoom process for photography standby ends because the effective magnification cannot be increased. When the current set magnification is not 6.0x, the routine advances to step S203.

When the set magnification is not 6.0x, the set magnification is increased one step (step S203).

Then, a determination is made as to whether or not the set magnification is greater than 3.0x (step S204). If the set magnification is greater than 3.0x, the routine advances to step S205, whereas when the set magnification is not greater than 3.0x, the routine advances to step S207.

When the set magnification is greater than 3.0x, the original image is subjected to thinness process based on the set magnification (step S205).

Then, the LCD automatic display process is executed (step S206).

For example, when the set magnification is 2.8x and the button 232 is pressed once, the optical zoom is

increased to 2.9x, and when pressed once more, the optical zoom is increased to 3.0x. Since the limit of the optical zoom is exceeded when the button 232 is pressed once more, both 3.0x optical zoom and electronic zoom controls are executed. If the LCD 10 display is OFF at this time, the LCD 10 is turned ON in addition to the warning. This process is the LCD automatic display control process. Details of the process sequence are described below.

FIG. 12 is a flow chart showing the process of the LCD automatic display control. In the LCD automatic display control process, it is necessary to start the LCD display with a set magnification of 3.1x, and, therefore a determination is made as to whether or not the set magnification is 3.1x (step S2061). When the set magnification is not 3.1x, the LCD automatic display control process ends, whereas when the set magnification is 3.1x, the routine advances to step S2062.

When the set magnification is 3.1x, a determination is made as to whether or not the LCD 10 is turned OFF (step S2062). If the LCD 10 is ON, the LCD automatic display control process ends, whereas when the LCD 10 is OFF, the routine advances to step S2063, and the LCD 10 is turned ON for display (step S2063).

The LCD automatic display control process ends, and the process ends when the set magnification is determined to be greater than 3.0x in the determination of step S204 of FIG. 11.

5                   Conversely, when the determination of step S204 is that the set magnification is equal to or less than 3.0x, the zoom motor 307 is driven one step to move the zoom lens 301 to the telecentric side (step S207), and the process of the photography standby ends.

10                   The process when the determination of step S204 is that the button 232 has not been pressed is described below.

15                   First, a determination is made as to whether or not the button 231 has been pressed (step S208). If the button 231 has not been pressed, there is not change to the set magnification, and the process of photography standby ends, whereas when button 231 has been pressed, the routine advances to step S209.

20                   When the button 231 has been pressed, a determination is made as to whether or not the current set magnification is 1.0x (step S209). When the current set magnification is 1.0x, the process of photography standby ends because a lesser magnification is impossible. When the current magnification is not 1.0x, the routine advances to step S210.

25

When the current set magnification is not 1.0x, the set magnification is decreased 1 step (step S210).

Then, a determination is made as to whether or not the set magnification is greater than 3.0x (step S211). When the set magnification is greater than 3.0x, the routine advances to step S212, whereas when the set magnification is not greater than 3.0x, the routine advances to step S231.

When the set magnification is greater than 3.0x, the original image is subjected to the thinness process based on the set magnification (step S212).

Conversely, when the set magnification is equal to or less than 3.0x, the zoom motor 307 is driven one step to move the zoom lens 301 to the wide side (step S213), and the process of photography standby ends.

Referring to FIG. 9, next, the LCD ON/OFF control process is executed (step S3). When the set magnification is 3.1x or greater, the LCD display is not always in the ON state, and a user may optionally set the LCD display to OFF. Regardless of the magnification, the LCD 10 ON/OFF state is switched each time the LCD button 321 is pressed. For this reason the LCD can be positively turned OFF to prevent battery consumption while being aware of the use of the electronic zoom.



The sequence of the LCD ON/OFF control process is described below. FIG. 13 is a flow chart showing the sequence of the LCD ON/OFF control process.

First, a determination is made as to whether or not the LCD button 321 has been pressed (step S301). If the LCD button 321 has not been pressed, the LCD ON/OFF control process ends, whereas when button 321 has been pressed, the routine advances to step S302.

When the LCD button 321 has been pressed, a determination is made as to whether or not the LCD 10 is turned OFF (step S302). If the LCD 10 is OFF, the routine advances to step S303, and the LCD 10 is turned ON for display (step S303). Conversely, if the LCD 10 is ON, the LCD 10 is turned OFF (step S304), and the LCD ON/OFF control process ends.

As can be understood from the zoom process during photography standby of FIG. 11 and the LCD ON/OFF control process described above, the LCD display ON/OFF state does not change even when the button 231 is pressed, and conversely changing from the telecentric side to the wide side, and the magnification is reduced sequentially step-by-step from 6.0x and from 3.1x to 3.0x. This arrangement is due to the strong unease when the LCD is suddenly turned OFF and mistaken belief of a power outage when framing a photo with the LCD 10, which adversely

affects operability. In the digital camera 1 of the present embodiment, such events are prevented.

Referring to FIG. 9, the warning LED control process is then executed (step S4). During electronic zoom, since the confirmable range by the optical finder does not match the actual photographic range, the warning LED 312 is always lighted when the set magnification is 3.1 or greater. The power consumption of the LED is not a problem even when always lighted because the power consumption is very slight compared to the LCD 10.

Details of the process sequence of the warning LED control process are described below. FIG. 14 is a flow chart showing the sequence of the warning LED control process.

First, a determination is made as to whether or not the set magnification is 3.1x or greater (step S401). If the set magnification is 3.1x or greater, the routine advances to S402, whereas when the set magnification is not 3.1x or greater, the routine advances to step S404.

When the set magnification is 3.1 or greater, a determination is made as to whether or not the warning LED 312 is OFF (step S402). If the warning LED 312 is ON, the warning LED control process ends, whereas when the warning LED 312 is OFF, it is turned ON (step S403), and the warning LED control process ends.

Similarly, even when the set magnification is less than 3.1x, a determination is made as to whether or not the warning LED 312 is OFF (step S404). If the warning LED 312 is OFF, the warning LED control process ends, whereas when the warning LED 312 is ON, the warning LED 312 is turned OFF (step S405), and the warning LED control process ends.

Referring to FIG. 9, then other processes are executed (step S5). This process is the basic process of the digital camera, and is a process of the photographic mode in which the auto exposure (AE) and autofocus (AF) are performed are by half pressing the shutter button 8. When the shutter button 8 is fully pressed, if necessary flash emission is performed, and image data (i.e., data subjected to the electronic zoom interpolation process) are compressed and recorded on the memory card. The process in the photographic mode is also executed in step S5.

Next, a determination is made as to whether or not the power switch 227 has been pressed (step S6). If the power switch has not been pressed, the routine returns to step S2, and until the power switch 227 has been pressed, the processes of steps S2-S5 are repeated. Then, when the power switch 227 is pressed, the routine advances to step S7.

When the power switch S7 is pressed, the current set magnification (effective magnification) is written to the flash ROM 211b, and the state of the LCD 10 display (ON/OFF) is written to the flash ROM 211b for use at subsequent start (step S7).

Finally, the power OFF process to turn OFF the power supply is executed (step S8).

This ends the description of the processes performed in the digital camera of the present embodiment.

According to the present embodiment as described above, during electronic zooming by pixel thinness or pixel interpolation by an expansion processor 211c used as an electronic zoom means, the LCD 10 is forcibly turned ON as an electronic finder regardless of the previous state. Therefore, since the LCD 10 has a zoom function corresponding to the effective magnification including the electronic zoom by the processing by the expansion processor 211c, the image of the photographic object corresponding to the effective sensing magnification during electronic zooming can be confirmed on the LCD 10 even when the optical finder 31 does not possess this zoom function. Accordingly, The compactness of the digital camera is not hindered, the photographic object is easily confirmed, and framing is simple. Furthermore, The electrical power of the digital

camera can be conserved by switching OFF the LCD 10 when electronic zoom is not used.

Since the warning LED 312 is lighted and the LCD 10 is turned ON when using the electronic zoom, the photographer is easily aware when electronic zoom is used.

Furthermore, when the effective magnification of the joint operation of the zoom lens 301 as an optical zoom means and the expansion processor 211c as an electronic zoom means is outside the magnification range obtainable by the optical finder 31 (specifically, when the effective magnification is greater than 3.0x), the warning LED 31 is lighted and the image is displayed on the LCD 10, such that the mismatch of the photographic range and the field of view of the optical finder 31 can be shown when using the optical finder 31.

Similarly, when the effective magnification of the joint operation of the zoom lens 301 and the expansion processor 211c is outside the magnification range obtainable by the optical finder 31 (specifically, when the effective magnification is greater than 3.0x), the LCD 10 is forcibly turned ON regardless of its previous state. In this way the mismatch of the photographic range and the field of view of the optical finder 31 can be shown by referencing the LCD 10 when using the optical finder 31.

Since the LCD 10 is forcibly turned ON when the starting magnification exceeds the range obtainable by the optical finder 31 when the digital camera is started, i.e., when the effective magnification is determined to be greater than 3.0x, the photographer can be alerted to the mismatch between the photographic range and the field of view of the optical finder 31 when the starting magnification exceeds the magnification obtainable by the optical finder 31.

Since the power OFF magnification of the previous power shutdown recorded in flash ROM 211b is set as the starting magnification, the photographer need not set the magnification of the previous power OFF because the starting magnification used is the magnification of the previous power OFF, thereby improving operability.

Since an operation switch is provided which is capable of turning OFF the LCD 10 when the LCD 10 is in the forced ON state, battery power consumption can be greatly conserved by turning OFF the power-draining LCD 10 with the full awareness of the mismatch of the photographic range and the field of view of the optical finder 31.

Since the photographer is warned by the lighting of the LED 312 and display on the LCD 10 when the starting magnification exceeds the magnification

range obtainable by the optical finder 31, the photographer is alerted to the mismatch of the photographic range and the field of view of the optical finder 31.

5                    Modifications

                  Although the digital camera and recording medium of the embodiments have been described by way of examples, the present invention is not limited to these examples.

10                   For example, although the warning LED 312 is lighted and displayed in the warning LED control process, the warning means may be suitably modified. For example, a speaker may be provided to issue an audible warning or warning sound. FIG. 15 shows a modification of the  
15                   warning means. This warning means is provided with a Porro prism 401 within the optical system of the optical finder, a transmission type LCD 402 disposed above the Porro prism 401, and a transparent window 403 provided on  
20                   the top surface of the image sensing unit 3 is disposed above the LCD 402. External light entering the window 403 is transmitted through the transmission type LCD 402, and arrives at the photographer side via the Porro prism 401. Then, when the electronic zoom is used, a warning  
25                   text is displayed on the transmission type LCD 402 and alerts the photographer. In this way the photographer

can confirm the warning text overlaid on the photographic object via the optical finder, thereby easily being made aware of the use of the electronic finder.

The position at which the warning means is provided is also optional. Specifically, the warning means may be disposed on the surface of the camera body 2 insofar as it is observable while looking in the optical finder.

In the above described embodiments, the electronic finder is turned ON when transitioning from a state of using the optical zoom alone to the state of using the optical zoom and electronic zoom in combination. However, the present invention is not limited to this arrangement, and the range of the art of the present invention further includes which zoom only using an electronic zoom wherein the electronic zoom is turned ON when transition from a state of no zoom to a state of using the electronic zoom.

In the above embodiments, when the set magnification (effective magnification) exceeds the upper limit magnification (3.0x) of the optical finder, the warning LED 312 is lighted, and the LCD 10 forcibly displays in warning. However, the present invention is not limited to this arrangement, inasmuch as the warning LED 312 may be lighted and LCD 10 forced to display in



warning when a specific lower limit different from 1.0x of the optical finder is set.

Although the upper limit magnification (zoom ratio) of the zoom lens 301 used as an optical zoom and the upper limit magnification (zoom ratio) of the optical finder 31 are both 3.0x in the above embodiments, these upper limits need not necessarily be identical. In this case, when, for example, the optical zoom magnification exceeds the zoom ratio of the optical finder, the warning LED 312 may be lighted and the display of the LCD 10 may be forced as an electronic finder.

Although the optical zoom is used in electronic zooming in the above embodiments, a mode may be provided for using electronic zoom alone. In this case, when the electronic zoom magnification exceeds the zoom ratio of the optical finder, the LCD 10 display may be forced as an electronic finder. Furthermore, while the above embodiments have been described as performing a pixel thinness process or pixel interpolation process after trimming the center area when using the electronic zoom, trimming may be performed alone.

Although the present invention has been fully described by way of examples with reference to the accompanying drawings, it is to be noted that various changes and modification will be apparent to those

skilled in the art. Therefore, unless otherwise such changes and modifications depart from the scope of the present invention, they should be construed as being included therein.